

FIRE ALARM BELL 6" UL

CATALOGUE Model. **ABUL1-13**

CERTIFICATE ISO 9001:2000/CE-CNS 12681

FOR USE

ALL FIRE ALARM SYSTEMS UL/NFPA



INSTALLATION NOTE

1. Remove a gong
2. Wire the bell in the circuit.
3. Mount bell mechanism on 4" square standard outlet box with the striker facing down
4. The bell must be mounted a minimum of 8ft., above the floor, or, as close to the ceiling as possible.
5. Polarized bell provides Red(+) and Black(-) lead wires. When you install the bell , must be observed the polarity

DESCRIPTION

Series bells are low current, high decibel notification appliances for use in fire and burhlarly systems or other signaling applications. The **SSM (24VDC) Series** is motor driven while the SSV (120VAC) Series utilizes a vibrating mechanism. The DC models are polarized for use with supervision circuitry.

SPECIFICATIONS

Sizes Available:	6" ,8" ,10"
Voltages Available:	24 VDC polarized, suppressed 20mA
Service Use	Fire alarm, general singaling, burglar alarm
Operating Temperatuer Range:	Indoor or outdoor use,- 31 to 140 F
Termination:	Provided with 2 sets of leads for in/out wiring
Alarm bell sound level	95 db /10ft

